

## PB-15ZW Panic Button

## Summoning Help with One Button Press



- Residential and commercial applications
- Waterproof to IPX4 standard
- Compatible with other manufacturers' Z-Wave systems
- OTA firmware update capability

The PB-15ZW panic button is designed for users to summon help with one simple button press when an emergency arises. In critical situations such as falls, acute medical problems, fires, or burglaries, users can quickly identify PB-15ZW's big red button and activate the device to report alarms to monitoring personnel.

The effective security solution provided by the PB-15ZW has residential and commercial applications. It can be installed in the homes of elderly individuals to make their independent living safer. It can also be used in gas stations, convenience stores, hospitals, or any other establishments where there are employees working at late hours. When pressed in times of distress, the button triggers a silent alarm to bring emergency assistance to users.

PB-15ZW is waterproof to IPX4 standard. By adopting Z-Wave Plus 500 series module, PB-15ZW is compatible with other manufacturers' Z-Wave systems. The panic button transmits supervisory and low battery signals to the security system to ensure its proper operation at all times.

### Features

- Big red button for quick identification and activation
- IPX4 water resistance rating
- LED indicator
- Regular supervision to check system integrity
- Over-the-Air (OTA) firmware update capability
- Compatible with other manufacturers' Z-Wave systems
- Low battery detection
- Classy design

### Specifications

Communication Protocol	Z-Wave Plus 500 series module
Frequencies	868.40 MHz (EU) / 908.40 MHz (US)
Power Source	3V, CR123 lithium battery x 1
Battery Life	3.7 years*
Operating Temperature	-10°C to 45°C (14°F to 113°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	74 mm x 46 mm x 22 mm

\*Note: Actual battery life may vary due to device settings, usage, and environment.